

أ.د/ صابر حلمي زين الدين



قسم هندسة الالكترونيات والاتصالات الكهربائية
صاحب فكرة البحث:- أ.د./ صابر حلمي زين الدين

قائمة تسجيل أبحاث

م	عناوين الأبحاث	أسماء المشاركين	تاريخ النشر
.1	<i>Dielectric Resonator Antenna Mounted on Cylindrical Ground Plane for Handheld RFID Reader at 5.8 GHz,</i> Advanced Electromagnetics Journal, Vol. 1, No. 3, pp. 71-78, October 2012.	S.H. Zainud-Deen, Hend A. Malhat, N. A. El-Shalaby, and K. H. Awadalla,	2012
.2	Novel Chipless Tag with Electromagnetic Code, The Middle East Conference on Antennas and Propagation (MECAP 2012)	S.H. Zainud-Deen, Hend A. Malhat, M.A. Abo-Elhassan and K.H. Awadalla,	2012
.3	Plasma Reflectarrays, The Middle East Conference on Antennas and Propagation (MECAP 2012)	S.H. Zainud-Deen, Hend A. Malhat, S.M. Gaber, M. S. Ibrahim, and K.H. Awadalla,	2012
.4	Perforated Convex and Concave Transmitarrays, The Middle East Conference on Antennas and Propagation (MECAP 2012)	S.H. Zainud-Deen, Hend A. Malhat, S.M. Gaber, and K.H. Awadalla,	2012

2012	S. H. Zainud-Deen, A. Mahmoud, A. Metkes, and A. Kishk	Wideband Rectangular Dielectric Resonator Elements Reflectarray, The Middle East Conference on Antennas and Propagation (MECAP 2012)	.5
2012	S.H. Zainud-Deen, Hend A. Malhat, S.M. Gaber, N.A. El-Shalaby and K.H. Awadalla,	Reflectarrays Mounted on or Embedded in Cylindrical and Spherical Surfaces, The Middle East Conference on Antennas and Propagation (MECAP 2012)	.6

البحث رقم (1)

Published In

Engineering Journal, SAP, vol. 2, No. 3, pp.88-95, 2012.

ADVANCED ELECTROMAGNETICS, Vol. 1, No. 3, October 2012

Title

Dielectric Resonator Antenna Mounted on Cylindrical Ground Plane for Handheld RFID Reader at 5.8 GHz

S. H. Zainud-Deen¹, H. A. Malhat², N. A. El-Shalaby³, and K. H. Awadalla⁴

^{1,2,4}Faculty of Electronic Engineering, Menoufia University, Egypt.

³Faculty of Engineering, Kafer Elshekh University, Egypt.

E-mail: 1anssaber@yahoo.com, 3noha1511ahm@yahoo.com,

4kamal_awadalla@hotmail.com

*corresponding author, E-mail: er_honida1@yahoo.com,

Abstract:

Dielectric resonator antenna (DRA) mounted on cylindrical ground plane is investigated for handheld RFID reader applications at 5.8 GHz. The simplicity of the structure makes it practical in terms of cost, space, and ease of fabrication. The radiation characteristics of the antenna in free space and in the presence of a proposed compact reader device model and human hand are calculated. The antenna is circularly polarized and exhibits peak gain of 7.62 dB at 5.8 GHz with high front to back ratio of 15.5 dB. Using the same reader device model, a sequentially feeding 2×2 DRA

array mounted on the same cylindrical ground plane is used for RFID reader antenna at 5.8 GHz. The array introduces high gain of 9.36 dB at 5.8 GHz with high front to back ratio of 10.48 dB. The 2×2 DRA array elements exhibit circular polarization over a frequency band of 1.1 GHz. The axial ratio is 1.1 dB at 5.8 GHz. The proposed reader model is simple and has a small size compared with that in the case of planar ground plane. The results are calculated using the finite element method (FEM) and compared with that calculated using the finite integral technique (FIT).

References

- [1] K. Finkenzeller, *RFID handbook: radio-frequency identification fundamentals and applications*, 2nd Ed., Wiley & Sons, Inc., New Jersey, USA, 2004.
- [2] B. Manish and M. Shahram, *RFID field guide: deploying radio frequency identification systems*, Prentice Hall PTR, 2005.
- [3] H. Bhatt, and B. Glover, *RFID essentials*, O'Reilly Media, Inc., Sebastopol, California, USA. 2006.
- [4] S.H. Zainud-Deen, S.M. Gaber, Hend A. Malhat, and K. H. Awadalla, " Multilayer dielectric resonator antenna transmitarray for near-field and far-field fixed RFID reader," *Progress In Electromagnetics Research C, PIER C*, vol. 27, pp. 129-142, 2012.
- [5] Z. Wu, and S. Lai, "Miniaturized microstrip array for the UHF-band RFID reader," *Microwave and Opt. Techol. Letters*, vol. 48, no. 7, pp. 1299-1301, July 2006.
- [6] Z. Sun, S. Zhong, X. Tang, and K. Chen, "Low side-lobe circular polarized microstrip array for 2.45 GHz RFID readers," *Microwave and Opt. Tech. Letters*, vol. 50, no. 9, pp. 2235-2237, September 2008.
- [7] Pavel V. Nikitin and K. V. S. Rao, "Helical antenna for handheld UHF RFID reader," *Proc. IEEE International Conference in RFID*, Orlando, FL., pp. 169-173, 2010.
- [8] B.Y. Feng, "A patch antenna for RFID reader," in *Proc. International Conference on Microwave and Millimeter*

Wave Technology, (ICM 2008), vol. 3, pp. 1044-1046, 2008.

[9] S. Kaki, and T. Chakravarty, "Compact printed Yagi antenna for handheld UHF-RFID reader," in Proc. Int. Conference on Devices and Communications (ICDeCom) Symp., pp. 1-3, 2011.

[10] K. M. Luk, and K. W. Leung, Dielectric resonator antenna, Hertfordshire, Research Studies Press, U.K, 2003.

[11] R. Chair, A.A. Kishk, and K.F. Lee, "Comparative study on the mutual coupling between different sized cylindrical dielectric resonator antennas and circular microstrip patch antennas ," IEEE Trans. Antennas Propag., vol. 53, no. 3, pp. 1011-1018, March 2005.

[12] A. Petosa, Dielectric resonator antenna handbook, Artech House Inc., Norwood, 2007.

[13] S. H. Zainud-Deen, Hend A. Malhat, and K. H. Awadalla, "Circular polarized dielectric resonator antenna for portable RFID reader using a single feed," International Journal of Radio Frequency Identification & Wireless Sensor Networks, vol. 1, no.1, 2011.

[14] S. H. Zainud-Deen, Hend A. Malhat, and K. H. Awadalla, "Dielectric resonator antenna mounted on a circular cylindrical ground plane," Progress In Electromagnetics Research B, PIER B, vol. 19, pp. 427-444, 2010.

[15] S. H. Zainud-Deen, Noha A. El-Shalaby, and K. H. Awadalla," Radiation characteristics of cylindrical dielectric resonator antenna mounted on superquadric cylindrical Body," Electrical and Electronic

[16] 27th Applied Computational Electromagnetics Society (ACES) Conference, Williamsburg, Virginia, USA, March 2011.

[17] S. H. Zainud-Deen, Noha A. El-Shalaby, and K. H. Awadalla," Hemispherical DRA antennas mounted on or embedded in circular cylindrical surface for producing omnidirectional radiation pattern". International Journal of Communication, Network and

System Sciences, vol.4, no.9, pp. 601-608, September 2011.

[18] D. V. Hutton, Fundamentals of finite element analysis, McGraw- Hills Companies, USA, 2004.

[19] S.J. Cooke, R. Shtokhamer, A.A. Mondelli, and B. Levush," A finite integration method for conformal, structured-grid, electromagnetic simulation," Journal of Computational Physics, vol. 215, pp. 321–347, 2006.

[20] A. A. Kishk, "Performance of planar four element array of single-fed circularly polarized dielectric resonator antenna," Microwave and Optical Technology Lett., vol. 38, no. 5, pp. 381-384, Sep. 2003.

[21] CST MICROWAVE STUDIO®, help, <http://www.cst.com>.

[22] S. H. Zainud-Deen, Hend A. Malhat, and K. H. Awadalla, "Circular polarized dielectric resonator antenna for portable RFID reader using a single feed," International Journal of Radio Frequency Identification & Wireless Sensor Networks, vol. 1, no.1, 2011.

[23] M. Haneishi, and h. Takazawa, "Broadband circularly polarized planar array composed of a pair of dielectric resonator antennas," Electronic Lett., vol. 21, no. 10, pp. 437-438, May 1985.

البحث رقم (2)

Title

NOVEL CHIPLESS TAG WITH ELECTROMAGNETIC CODE

, S.H. Zainud-Deen¹, M. Abo El-Hassan, H.A. Malhet² and K.H. Awadalla

Faculty of Electronic Eng., Menoufia University, Egypt

2er_honida1@yahoo.com lanssaber@yahoo.com,

Keywords:

Radio Frequency Identification, chipless tag,
curved surface.

Abstract:

This paper presents a new radio frequency identification (RFID) chipless tag operating in the frequency span 4-7 GHz. The tag consists of triangle microstrip filter. The bits are encoded into the spectrum hence the tag has a unique spectral signature. The tag is less sensitive to tag orientation and has smaller size. A 6-bit chipless tag is designed. The simple opening of the triangle sides shifts the resonant frequency of the triangle resonator to an insignificant frequency, which is not used in the band. The curvature effects on the characteristics of the filter are analysed. The chipless tag is designed for advanced traffic and vehicle regulation, alarm and navigation. The finite-element method and the finiteintegration technique are used to investigate the

characteristics of the filter.

References

- [1] H. Stockman, "Communication by means of reflected power," , Proceedings of the IRE, pp. 1196-1204, October 1948.
- [2] S. Preradovic, and N.C. Karmakar, "Chipless RFID tag with integrated sensor," IEEE Sensors, Kona, HI, pp. 1277-1281, 2010.
- [3] S. Preradovic, and N.C. Karmakar, "Chipless RFID: barcode of the future," IEEE Microwave Magazine, pp. 87-97, December 2010.
- [4] S. Preradovic, S.M. Roy, and N.C. Karmakar, "RFID system based on fully printable chipless tag for paper-plastic-item tagging," IEEE Antennas and Propagation Magazine, vol.53, no.5, pp.15-32, October 2011.

- [5] S. Preradovic, and N .Karmakar, Multiresonator-Based Chipless RFID, Springer Science, London, England, 2012.
- [6] C.S. Hartmann, “A global SAW ID tag with large data capacity,” in Proc. IEEE Ultrason. Symp., Munich, Germany, October 2002.
- [7] J. McVay, A. Hoorfar, and N. Engheta, “Space-filling curve RFID tags,” in IEEE Radio Wireless Symp., San Diego, CA, pp. 199-202, 2006.
- [8] I. Jalaly and D. Robertson, “Capacitively-tuned split microstrip resonators for RFID barcodes,” in Eur. Microw. Conf., Paris, France, vol.2, pp. 4-7, 2005.
- [9] S. Preradovic, I. Balbin, N.C. Karmakar, and G.F. Swiegers, “Multiresonator-based chipless RFID system for low-cost item tracking,” IEEE Transactions on Microwave Theory and Techniques, vol.57, no.5, pp. 1411-1419, May 2009.
- [10] S. Preradovic, N.C. Karmakar, and E. Md. Amin, “Chipless RFID tag with integrated resistive and capacitive sensors,” Proceedings of the Asia-Pacific Microwave Conference, Australia, pp. 1354,-1357, 2011.
- [11] A. C. Polycarpou, Introduction to the Finite Element Method in Electromagnetics, Morgan & Claypool, USA, 2006.
- [12] M. Clemens, and T. Weiland, “Discrete Electromagnetism With The Finite Integration Technique,” Progress In Electromagnetics Research, PIER, Vol. 32, pp. 65- 87, 2001.

البحث رقم (3)

Title

PERFORATED CONVEX AND CONCAVE TRANSMITARRAYS

S.H. Zainud-Deen¹, S.M. Gaber², H.A. Malhet¹, M. Ibrahim³, and K.H. Awadalla¹

¹Faculty of Electronic Eng., Menoufia University, Egypt, er_honida1@yahoo.com

²Egyptian Russian University, Egypt, shaymaa.gaber@yahoo.com

³MUST University, 6 oct., Egypt, mourad_said1@hotmail.com

Keywords:

perforated dielectric material, Transmitarray,
satellite applications.

Abstract:

In this paper, the radiation characteristics of curvature transmitarray is investigated. Concave and convex transmitarrays are designed and analysed using the finite integral technique. Centre and offset beams transmitarrays are considered for satellite applications at 10 GHz. Perforated technique is used to construct the concave and convex transmitarray from a single dielectric sheet. A 13x13 unit cell element is designed to operate at 10GHz for each concave and convex transmitarray. The radiation characteristics of the concave and convex transmitarray with different focal to diameter ratio and different subtended angles are investigated and compared with that of the planar transmitarray.

References:

- [1] J. Huang and J. A. Encinar, *Reflectarray Antennas*, John Wiley & Sons Inc., Hoboken, NJ, USA, 2007.
- [2] K-W. Lam, S.-W. Kwok, Y. Hwang, and T. Lo, "Implementation of transmitarray antenna concept by using aperture coupled microstrip patches," *APMC Hong Kong*, pp. 433-436. 1997.
- [3] M.R. Chaharmir, A. Ittipiboon, J. Shaker, "Single-band and dual-band transmitarray," *ANTEM 2006*, Montreal, QC, 2006.
- [4] W. X. Zhang, D. L Fu, A. N. Wang, "A compound printed air-fed array antenna," *2nd European Conf. on Antennas and Propag.*, (EuCAP 2007), pp. 1054-1057, 2007.

- [5] S. H. Zainud-Deen, Sh. M. Gaber, and K. H. Awadalla, "Rectangular Dielectric Resonator Transmitarrays," 29th National Radio Science Conference (NRSC), Egypt, 2012.
- [6] A. Capozzoli, C. Curcio, G. D'Elia, and A. Liseno, "Fast phase-only synthesis of conformal reflectarrays," IET Microw. Antennas Propag., vol.4, no.12, pp.1989-2000, 2010.
- [7] P. Nayeri, F. Yang, and A.Z. Elsherbeni, "Radiation characteristics of conformal reflectarray antennas," IEEE Symobozym 2011.
- [8] [8] A. Petosa, A. Ittipiboon, S. Thirakoune, "Perforated dielectric resonator antennas," Electronics Letters, vol. 38, no. 24, pp. 1493 – 1495, December, 2002
- [9] A. Petosa, S. Thirakoune, and A. Ittipiboon, "Array of perforated dielectric resonator antennas," Proc. IEEE Antennas and Propagation Soc. Int. Symp., USA, vol. 10, pp. 1106 – 1109, June 2004.
- [10] R. Chair, A.A. Kishk, and K.F. Lee, "Experimental investigation for wideband perforated dielectric resonator antenna," Electronic Letters, vol. 42, no. 3, pp. 137-139, Feb. 2006
- [11] A.M. Abd-Elhady, and Wei.Hong, "Ka-Band Linear Polarized HoleReflectarray," 1st Middle East Conf. on Antennas and Propag, IEEE APS, Egypt, pp.1-14, October.2010.
- [12] M. M. Fard, and M. K. Amirhosseini," Perforated reflectarray antennas," Journal of telecommunication, vol. 3, no.7, pp.17-22, July.2010.
- [13] S. H. Zaiund-Deen, S. M. Gaber, A. M. Abd-Elhady, A. A. Kishk, and K.H. Awadalla, " Wideband perforated rectangular dielectric resonator antenna reflectarray," in Proc. IEEE Antennas and Propagation Soc. Int. Symp., USA, vol. 1, pp. 113-116, June 2011.
- [14] S. H. Zainud-Deen, Sh. M. Gaber, and K. H. Awadalla, "Transmitarray Using Perforated Dielectric Material For Wideband Applications , " Progress In Electromagnetics Research, PIER M, vol. 24 , pp. 1-13 , 2012.
- [15] R. Schuhmann, T. Weiland, W.H. Schilders, E.J. Maten, and S.H. Houben, "Recent advances in finite integration technique for high frequency applications," Scientific

Computing in Electrical Engineering, vol. 4, pp. 46-57,
2004.

[16] D. V. Hutton, Fundamentals of finite element analysis,
McGraw- Hills Companies, USA, 2004.

[17] Y. Zhang, and A.A. Kishk, “Analysis of dielectric
resonator antenna arrays with supporting perforated
rods,” 2nd European Conf. on Antennas and Propag.,
(EuCAP 2007), pp. 1-5, 2007.

البحث رقم (4)

Title

PLASMA REFLECTARRAYS

S.H. Zainud-Deen¹, H.A. Malhet¹, S.M. Gaber², M. Ibrahim³, and K.H. Awadalla¹

¹Faculty of Electronic Eng., Menoufia University, Egypt, er_honida1@yahoo.com

²Egyptian Russian University, Egypt, shaymaa.gaber@yahoo.com

³MUST University, 6 oct., Egypt, mourad_said1@hotmail.com

Keywords:

Plasma antenna, Reflectarray, satellite

applications.

Abstract:

This paper investigates the design of four different configurations of plasma reflectarrays. The results provide insight into different radiation characteristics of plasma reflectarrays. The proposed unit cell consists of cubic glass box filled with Argon gas energized with applied AC voltage.

The reflectarray reflection coefficients phase variation is achieved by varying the plasma frequency of the energized gas. Four plasma reflectarrays for satellite applications at 12 GHz are proposed (centre-feed centre-beam, centre-feed offset-beam, offset-feed centre-beam, and finally offset-feed offset-beam). The finite integration technique is used to analyze the plasma reflectarray

References :

- [1] Z.N. Chen, *Antennas for portable devices*, Wiley & Sons, Inc., England, 2007.
- [2] J. Huang and J.A. Encinar, *Reflectarray antennas*, John Wiley and Sons, Inc., Hoboken, NJ, USA, 2007.
- [3] S. H. Zainud-Deen, E. Abd, A. A. Mitkees, and A. A. Kishk, "Design of dielectric resonator reflectarray using full-wave analysis," in National Radio Science Conference (NRSC 2009), pp. 1-9, Egypt, 2009.
- [4] D. Cadoret, L. Marnat, R. Loison, R. Gillard, H. Legay, and B. Salome, "A dual linear polarized printed reflectarray using slot loaded patch elements," The 2nd European Conference Antenna and Propagation (EUCAP 2007), pp. 1-5, 2007.
- [5] T. Anderson, *Plasma antennas*, Artech House, Norwood, England, 2011.
- [6] D. H. Froula, S. H. Glenzer, N. C. Luhmann, and J. Sheffield, *Plasma scattering of electromagnetic radiation*, Elsevier Inc., Burlington, USA, 2011.
- [7] R.J. Vidmar, "On the use of atmospheric pressure plasmas as electromagnetic reflectors and absorbers," IEEE Trans. Plasma Sci., vol.18, no.4, pp. 733-741, August 1990.
- [8] W.W. Destle, J.E. Degrange, H.H. Fleischmann, J. Rodgers, and Z. Segalov, "Experimental studies of high power microwave reflection, transmission, and absorption from a plasma-covered plane boundary," Journal of Applied Physics, vol. 69, pp. 6313-6318, 1991.

- [9] X.P. Wu1, J.M. Shi, Z.S. Chen, and B. Xu, "A new plasma antenna of beam-forming" Progress In Electromagnetics Research (PIER), vol. 126, pp. 539-553, 2012
- [10]Z.H. Qian, K.W. Leung, R.S. Chen, and D.X. Wang "FDTD analysis of a plasma whip antenna," in IEEE International Symposium of Antennas and Propagation Soc., pp. 166-169, 2005.
- [11]Y. Bo, Y. Feng, W. Bin, and H. Hong, "Mutual impedance of plasma antennas," in 7th International Conference on Wireless Communications, Networking and Mobile Computing (WiCOM 2011), pp. 1-4, 2011.
- [12] I. Alexeff, T. Anderson, S. Parameswaran, E.P. Pradeep, J. Hulloli, and P. Hulloli, "Experimental and theoretical results with plasma antennas," IEEE Trans. Plasma Sci., vol.34, no.2, pp. 166-172, April 2006.
- [13]Alexeff, T. Anderson, and S. Parameswaran, "Advances in plasma antenna design," in IEEE International Conference on Plasma Science, (ICOPS 2005), pp. 350-350, 2005.
- [14]R. Marklein, The finite integration technique as a general tool to compute acoustic, electromagnetic, elastodynamic, and coupled wave fields, IEEE Press, , pp 201–244, New York, USA, 2002.
- [15]CST Microwave Studio – Workflow and Solver Overview, 2010.

البحث رقم (5)

Title

Reflectarrays Mounted on or embedded in Cylindrical or Spherical Surfaces

S.H. Zainud-Deen¹, N.A. El-Shalaby², S.M. Gaber³ H.A. Malhet¹, and K.H. Awadalla¹

¹Faculty of Electronic Eng., Menoufia University, Egypt.

²Kafer El-Sheikh University, Egypt, ³Egyptian Russian University, Egypt.

Keywords:

Reflectarray, Dielectric Resonator.

Abstract:

In this paper, reflectarrays mounted on or embedded in cylindrical or spherical surfaces are designed, analyzed, and simulated at 11.5 GHz for satellite applications. The effect of the cylindrical or spherical surfaces curvature with different subtended angles on the radiation characteristics of the designed reflectarrays are investigated and compared with that of planar reflectarray. Full-wave analysis using the finite integration technique (FIT) is applied. The impedance matching bandwidth is greater than 3 GHz. The results are validated by comparing with that calculated by transmission line method (TLM).

References:

- [1] L. Josefsson and P. Persson, Conformal array antenna theory and design, (IEE Press Series on Electromagnetic Wave Theory), Wiley-Interscience, 2006.
- [2] J. Huang and J.A. Encinar, Reflectarray antennas, John Wiley and Sons, Inc., Hoboken, NJ, USA, 2007.
- [3] S. H. Zainud-Deen, E. Abd, A. A. Mitkees, and A. A. Kishk, "Design of dielectric resonator reflectarray using full-wave analysis," in National Radio Science Conference (NRSC 2009), pp. 1-9, Egypt, 2009.
- [4] D. Cadoret, L. Marnat, R. Loison, R. Gillard, H. Legay, and B. Salome, "A dual linear polarized printed reflectarray using slot loaded patch elements," The 2nd European Conference Antenna and Propagation (EUCAP

2007), pp. 1-5, 2007.

[5] R.C. Hansen, *Phased array antennas*, John Wiley & Sons, 1998.

[6] A. Capozzoli, C. Curcio, G. D'Elia, and A. Liseno, "Fast phase-only synthesis of conformal reflectarrays," *IET Microw. Antennas Propag.*, vol.4, no.12, pp.1989-2000, 2010.

[7] C. Tienda, et al., "Analysis of a dual-reflect array antenna," *Microwaves, Antennas & Propagation*, IET, vol. 5, pp. 1636-1645, 2011.

[8] P. Nayeri, F. Yang, and A.Z. Elsherbeni, "Radiation characteristics of conformal reflectarray antennas," *IEEE Symposium 2011*. (The details for this reference are to be completed.)

[9] T. Weiland, "A discretization method for the solution of Maxwell's equations for six-component fields," *Electronics and communications*, AEU, vol.31, no.3, pp. 116-120, March 1977.

[10]C. Christopoulos, *The transmission line modeling method (TLM)*, The Institute of Electrical and Electronics Engineers, Inc., 1995

[8] P. Nayeri, F. Yang, and A.Z. Elsherbeni, "Radiation characteristics of conformal reflectarray antennas," *IEEE Symposium 2011*. (The details for this reference are to be completed.)

[9] T. Weiland, "A discretization method for the solution of Maxwell's equations for six-component fields," *Electronics and communications*, AEU, vol.31, no.3, pp. 116-120, March 1977.

[10]C. Christopoulos, *The transmission line modeling method (TLM)*, The Institute of Electrical and Electronics Engineers, Inc., 1995.

البحث رقم (6)

Title

Wideband Rectangular Dielectric Resonator Elements Reflectarray

Abd-Elhady. M.1, S.H. Zainud-Deen2, A.A. Mitkees3, and A.A. Kishk4

1Faculty of Engineering, Banha University, Egypt

2Faculty of Engineering, Elmenoufia University, Egypt

3Military Technical College, Egypt

4Department of Electrical Engineering, University of Concordia, Canada

abdoeng78@gmail.com, anssaber1@yahoo.com, aamitkees@yahoo.com,

kishk@enes.concordia.ca

Keywords:

DR_A, Reflectarray, Planar array.

Abstract:

In this paper, two identical rectangular DRAs are used as a unit cell in the reflectarray structure. The proposed reflectarray has broadband characteristics covering the Xband and Ku-band. Full-wave analysis using finite integral technique (FIT), finite element method (FEM) and

transmission line method (TLM) are used.

References:

- [1] J. Huang and J.A. Encinar, *Reflectarray antennas*, John Wiley & Sons, Inc., Publication, 2008.
- [2] J. Huang, "Microstrip reflectarray," IEEE Int. Symp. on Antennas and Propagat., Ontario, Canada, pp.612-615, June 1991.
- [3] S. Datthanasombat, A.Jr. Prata, P. Brown, O. Quintero, S. Spitz and E. Rodriguez, "Spiral microstrip patch element for reflectarrays," IEEE Int. Symp. on Antennas and Propagat., vol.3, pp.721-724, July 2001.
- [4] C. Han and K. Chang, "Ka-band reflectarray using ring elements," Electron. Lett., vol.39, no.6, pp.491-93, March 2003.

- [5] K.Y. Sze and L. Shafai, "Hat-shaped patches for linesource-fed microstrip reflectarray," *Electron. Lett.*, vol.37, no.15, pp.937-939, July 2001.
- [6] M. Bozzi, S. Germani and L. Perregrini, "Performance comparison of different element shapes used in printed reflectarrays," *IEEE Int. Symp. on Antennas and Propagat.*, vol.3, pp. 294-297, June 2003.
- [7] D.M. Pozar and S.D. Targonski, "A microstrip reflectarray using crossed dipoles," *IEEE Int. Symp. on Antennas and Propagat.*, vol.2, pp.1008-1011, June 1998.
- [8] R.D. Javar, X.-D. Wu, and K. Chang, "Offset-feed microstrip reflectarray antenna," *Electron. Lett.*, vol.30, no.17, pp.1363-1365, August 1994.
- [9] D.I. Wu, R.C. Hall and J. Huang," Dual-frequency microstrip reflectarray," *IEEE Int. Symp. on Antennas and Propagat.*, vol.4, pp. 2128-2131, June 1995.
- [10] D. Pilz and W. Menzel, "Folded reflectarray antenna," *Electron. Lett.*, vol.34, no.9, pp.1326-1329, July 1996.
- [11] M.E. Bialkowski and H.J. Song, "Dual linearly polarized reflectarray using aperture coupled microstrip patches," *IEEE Int. Symp. on Antennas and Propagat.*, vol.3, pp. 486-489, July 2001.
- [12] J.A.Encinar, "Design of two- layer printed reflectarrays using patches of variable size," *IEEE Trans. Antennas Propagat.*, vol.49, no.10, pp. 1403–1410, Oct.2001.
- [13] C.Han, C. Roden beck, J.Huang and K.Chang , "A C/Ka dual frequency dual layer circularly polarized reflectarray antenna with microstrip ring elements," *IEEE Trans. Antenna Propagat.*,vol.52,no.11,pp.2871–2876, Nov. 2004.
- [14] J.A.Encinar and J.A.Zornoza, "Three-layer printed reflectarrays for contoured beam space applications," *IEEE Trans. Antennas Propagat.*, vol.52, no.5, pp.1138–1148, May 2004.
- [15] H. Deguchi, T. Idogawa, M. Tsuji and H. Shigesawa, "Offset reflectarrays with dense microstrips for wideband use, " *Proceedings of ISAP2005*, vol. 1, pp. 229–232, Aug. 2005.
- [16] S.Sakita, H.Deguchi, and M.Tsuji, "Single-layer microstrip reflectarray based on dual-resonance behavior," *Proc. of ISAP 2007*, vol.1, pp.1290 – 1293, Aug.2007.
- [17] K.Mayumi, H.Deguchi, and M.Tsuji, "Wideband singlelayer microstrip reflectarray based on multiple resonance

behavior," in IEEE Int. Symp. Antennas Propagat., pp .432-434, July2008.

[18] R.Chaharmir ,J.Shaker ,M.Cuhaci ,and A.Ittipiboon , "Broadband reflectarray antenna with double cross loops," Electron.Lett.,vol.42, no.2 , pp.65–66,2006.

[19] R.Chaharmir ,and J.Shaker , " Broadband reflectarray antenna with combination of cross and rectangular loop elements , " Electron.Lett.,vol.44,no.11,2008.

[20] M. G. Keller, J. Shaker and A. Petosa, A. Ittipiboon, M. Cuhaci, Y. M. M. Antar, "A Ka-band dielectric resonator antenna reflectarray", European Microwave Conference 2000, Paris, France, pp. 272-275, Oct. 2000.

[21] S.H. Zainud-Deen, A.M. Abd-Elhady, A.A. Mitkees and A.A. Kishk, "Design of Dielectric Resonator Reflectarray Using Full-Wave Analysis," 26th National Radio Science Conference (NRSC 2009), Egypt, B10, pp. 1-9, March 2009.

[22] S.H. Zainud-Deen, A.M. Abd-Elhady, A.A. Mitkees and Ahmed A. Kishk, "Dielectric Resonator Reflectarray with Two DRA Sizes and Varying Slot Loading," 2010 IEEE AP-S International Symposium on Antennas and Propagation and USNC/URSI National Radio Science Meeting, Toronto, Canada, 2010.

[23] S.H. Zainud-Deen, A.M. Abd-Elhady, A.A. Mitkees and Ahmed A. Kishk, "Slot-Loading Rectangular Dielectric Resonator Elements Reflectarray",1st Middle East Conference on Antennas and Propagation, (MECAP), Cairo, Egypt, Oct. 2010.

[24] A.M. Abd-Elhady, S.H. Zainud-Deen, A.A. Mitkees and Ahmed A. Kishk, "X-Band Linear Polarized Aperture-Coupled DRA Reflectarray," 2010 International Conference on Microwave and Millimeter Wave Technology, Chengdu, China, 2010.

[25] CST microwave studio 2009.

[26] HFSS v11.0.2., Ansoft Corporation, 2007.
